INSTRUCTION SHEET



ROOK REMOTE FLUSH WALL MOUNT (ADA COMPLIANT)

689-0793

PAGE 1 OF 1

WARNING - RISK OF FIRE AND ELECTRICAL SHOCK. FIXTURE MUST BE INSTALLED BY A QUALIFIED ELECTRICIAN ONLY. FIXTURE IS INTENDED FOR INSTALLATION IN ACCORDANCE WITH THE NATIONAL ELECTRICAL CODE, LOCAL AND FEDERAL SPECIFICATIONS. DISCONNECT POWER AT ELECTRICAL PANEL BEFORE SERVICING. **RETAIN THESE INSTRUCTIONS FOR MAINTENANCE REFERENCE. 1** MOUNT PLATE 2 REMOVE CORE 0 ß FIXTURE HOUSING MOUNTING HOLES MOUNTING HARDWARE x2 (BY AMERLUX) FIXTURE HOUSING 18/2 CORD FROM POWER SOURCE TOP FIXTURE SCREWS (x2) MOUNTING PLATE FIXTURE CORE 4" X 2-1/8" JUNCTION BOX RECESSED 1/8" - 3/8" INTO WALL (BY OTHERS) LOOSEN (DON'T REMOVE) TOP FIXTURE SCREWS, ROTATE SCREWS ALONG RADIAL KEYSLOTS, THEN PUSH SCREWS THROUGH KEYSLOT FEED 18/2 CORD THROUGH MOUNTING PLATE CENTERHOLE, THEN OPENINGS (REFER TO 689-0764 FOR FURTHER INSTRUCTION) ATTACH MOUNTING PLATE AS SHOWN TO J-BOX WITH HARDWARE **3** MOUNT HOUSING **4** RE-INSTALL CORE WING NUTS (x2) (BY AMERLUX) LED LED + RED/WI <u>BLK/WH</u> FEED 18/2 CORD THROUGH HOUSING CENTERHOLE, ALIGN (x2) HOUSING MOUNTING HOLES TO MOUNTING PLATE STUDS, MAKE ELECTRICAL CONNECTION WITH SUPPLIED WAGOS, PUSH HOUSING FLUSH AGAINST WALL, THEN THREAD WING NUTS THEN INSERT CORE INTO FIXTURE AND ROTATE TOP FIXTURE ONTO MOUNTING PLATE STUDS AND FULLY TIGHTEN SCREWS IN KEYSLOTS AND FULLY TIGHTEN Amerlux, 178 Bauer Drive, Oakland, N.J. 07436, T: 973-882-5010, F: 973-882-2604 www.amerlux.com

REVISION

DATE

APPROVED